

The **CableVista** Edge Decoder performs MPEG decoding, modulation and upconversion for up to 24 NTSC/PAL channels in a compact 1 RU chassis. The CableVista supports a variety of output card types in the same chassis including: Baseband NTSC/PAL, RF NTSC/PAL, RF NTSC with Off Air Reference. The CableVista provides customers with the highest degree of flexibility available. With numerous redundancy features, hot-swappable components and flexible software, the CableVista is the key element in today's Digital Simulcast network.



Key Features

- Multiple output card types available:
 - MPEG to Base Band (NTSC or PAL)
 - MPEG to RF Channels (NTSC or PAL)
- EAS support as per SCTE 18 (NTSC BB or RF output cards only)
- VITS insertion (NTSC BB or RF output cards only)
- Modular chassis fits up to 6 output cards and can provide:
 - Up to 12 Base Band channels decoded in 1RU
 - Up to 24 RF channels decoded in 1RU
 (*Mixing output cards of different types in a single chassis is also possible*)
- Internal CLI Tagging (NTSC version only)
- Off Air Reference/Phase Lock (CV1116RF/OAPL)
- GbE Redundancy
- ASI Inputs
- Output module redundancy
- GbE or ASI daisy chaining of several CableVista units possible
- All modules and power supplies are hot-swappable
- IGMPv3 support
- Configuration and control via Web page interface
(*Configuration and control also available through RS232 or SNMP*)
- Field upgradable firmware to incorporate new features

Optimized for Gigabit Ethernet Networking

- Full line rate GbE video transport allowing full use of GbE links

“Pay as You Grow” Modularity

- Modular design allows for more output cards to be added as demand grows

High Availability

- Output cards are hot swappable allowing installation or replacement on active systems
- Costly service outages are minimized, uptime is maximized
- Enhanced system reliability: redundant GbE ports, cooling fans, dual power supplies

Extremely High Density

- Up to 12 Base Band or 24 RF channels in 1RU
- Fully tested and interoperable with industry leading networking equipment

GbE Input

Interface	GbE (1+1 Redundant) SFP module (optical or copper)
Data Rate	1 Gbps
Format	MPEG-2 Transport Streams 188-byte TS Packets Unicast and Multicast

ASI Input

Number of Input Ports	2
Connector	BNC
Data Rate per port	210 Mbps
Packet Data Format	188 or 204 bytes/packet
Standard	EN50083-9

ASI Output for Loop Through

Number of Output Ports	1
Connector	BNC
Data Rate per port	210 Mbps
Packet Data Format	188 or 204 bytes/packet
Standard	EN50083-9

Video and Audio

Video Format	MPEG-2, MP@ML up to full D1 resolution
Audio Formats	Dolby Digital (AC-3) MPEG-1 layer 2 (Musicam)

Management and Control

Interface	RJ-45 (10/100 Ethernet) RS-232 (Console Port) SNMP
Protocols	Web Based Interface DHCP/BootP TFTP IGMPv3 Telnet

Power

Input Frequency Range	50/60 Hz
Input Voltage Range	100 to 240 VAC
Power Consumption	331 W maximum (decoding of 24 channels)

General

Chassis Width	19"
Chassis Height	1.75" (1RU)
Chassis Depth	23"
Weight (fully loaded chassis)	26 lbs
Operating Temperature Range	10°C to 40°C
Humidity Range (non-condensing)	10-90%

NTSC

Emergency Alert Messaging

Standard	As per SCTE 18
In-Band Reception	via GbE Input
Out-of-Band Reception	via 10/100 Ethernet

VITS Insertion

Test Patterns	NTC7 Composite, SMPTE Color Bars, Multiburst, Sin(x)/x, FCC Composite, NTC7 Combination, Modulated Ramp, Black Burst, Shallow Ramp
VBI Lines	17 - 20

CLI Tagging

Modulation Type	AM or Carrier Frequency Offset
AM Modulation Freq.	1 to 30 Hz
Depth of AM Modulation	0 to 90%
Carrier Freq. Range	54 to 900 MHz
	88 to 900 MHz (CV1146RF only)
Carrier Freq. Offset	-12.5 kHz or -25 kHz
Carrier Freq. Power Offset	-14 dB to 3 dB

Closed Caption / VBI Processing

Input Format	As per ANSI/SCTE 20 2004 or ANSI/SCTE 21 2001
Closed Captioning Format	As per EIA608 (Line 21)

Optional Configurations

- Dual Power Supplies for Redundancy
 - -48VDC Power Supply
 - Output Modules: Minimum 2 up to a maximum of 6
- Any combination of the following output cards can be used in the same CableVista chassis:**

CV1120BB
CV1116RF/OAPL
CV1126RF
CV1146RF

PAL B/G


Teletext / VBI Processing

Input Format	As per EN 301 775
Teletext (WST-B) Output	As per ITU-R BT 653-2 (Line 7 to 22)
WSS Output	As per EN 300 294


Optional Configurations

- Dual Power Supplies for Redundancy
 - -48VDC Power Supply
 - Output Modules: Minimum 2 up to a maximum of 6
- Any combination of the following output cards can be used in the same CableVista chassis:**

CV1121BB
CV1128RF/PBGN
CV1128RF/PBGF
CV1148RF/PBGN



CableVista CV1100 - Front



CableVista CV1100 - Rear
(1RU chassis accommodates 2 to 6 output cards)



Provided by: Mega Hertz
Bringing Next Generation Video to Life!™

(800) 883-8839

(303) 779-1749

sales@go2mh.com

www.go2mh.com

cv1100_br_14

Copyright © Vecima Networks Inc. Vecima reserves the right to modify or discontinue any product or piece of literature at anytime without prior notice. All Trademarks are property of their respective owners. Compliance with export control laws: Various export control laws of Canada, the United States or other countries may restrict or prohibit the export to certain countries of products sold by Vecima. Vecima shall not be liable for anything arising from compliance, or efforts to comply, with export control laws.